

WHAT IS CLAIMED IS:

1. A method of providing corrected values of gain and level coefficients of a set of correction coefficients for a scanning detector array, the scanning detector array comprising a plurality of detector channels, the method
5 comprising the steps of:
modifying first values of the gain and level coefficients using at least one frame of image data collected by the scanning detector array from out-of-focus multiple-temperature imagery; and
determining updated values of the gain and level coefficients using a
10 scene-based non-uniformity correction (SBNUC) routine applied to scene data corresponding to focused scene imagery.
2. The method of claim 1, wherein the step of modifying first values of the gain and level coefficients comprises applying said SBNUC routine to the frame of image data collected from out-of-focus multiple temperature imagery.
- 15 3. The method of claim 1, wherein said step of determining updated values of the gain and level coefficients using the SBNUC routine comprises the steps of:
acquiring a frame of said scene data corresponding to focused scene imagery;
20 applying a response correction to the frame of scene data using existing values of the gain and level coefficients to provide a corrected frame of scene data;
adjusting the existing values of the gain and level coefficients using the the SBNUC routine applied to the corrected frame of scene data, wherein the existing values of the gain and level coefficients are replaced with updated values.

4. The method of claim 3, wherein said step of adjusting the existing values of the gain and level coefficients is carried out while displaying a corrected scene image corresponding to the corrected frame of scene data.

5. The method of claim 3, wherein the set of correction coefficients includes moment coefficients, and wherein said step of applying a response correction to the frame of scene data includes using the moment coefficients.

6. The method of claim 3, wherein the step of adjusting the existing values of the gain and level coefficients using the SBNUC routine comprises the steps of:

10 generating a preliminary level correction factor for each detector channel using a frame of scene data;

generating a gain correction factor for each detector channel using the frame of scene data;

15 generating a gain-induced level correction factor for each detector channel based upon the gain correction factor; and

updating the existing values of the gain and level coefficients for each detector channel using the preliminary level correction factor, the gain-induced level correction factor, and the gain correction factor for each channel.

7. The method of claim 6, wherein the step of updating the existing values of the gain and level coefficients comprises:

adding the preliminary level correction factor and the gain-induced level correction factor for each channel, thereby forming a sum corresponding to each detector channel;

25 subtracting the sum from the existing value of the level coefficient for each detector channel to form the updated value of said level coefficient; and

multiplying the existing value of the gain coefficient for each channel by the gain correction factor corresponding to that channel to form the updated value of the gain coefficient for each detector channel.

5 8. The method of claim 3, wherein said steps of acquiring a frame of scene data, applying a response correction, and adjusting the existing values of the gain and level coefficients are carried out sequentially in that order.

10 9. The method of claim 8, wherein said steps of acquiring a frame of scene data, applying a response correction, and adjusting the existing values of the gain and level coefficients are repeated iteratively such that the updated values of the gain and level coefficients converge to respective stable values.

15 10. The method of claim 1, further comprising:
adjusting initial values of the level coefficients of the set of correction coefficients using an initial frame of image data collected by the scanning detector array from a predetermined source, said adjusting providing the first values of the level coefficients.

11. The method of claim 10, wherein the predetermined source is a bland source having a substantially uniform spatial structure and a substantially uniform temperature.

20 12. A scene-based non-uniformity correction (SBNUC) method for correcting values of gain and level coefficients of a set of correction coefficients for a scanning detector array, the scanning detector array comprising a plurality of detector channels, the method comprising the steps of:

generating a preliminary level correction factor for each detector channel using a frame of input scene data;

generating a gain correction factor for each detector channel using the frame of input scene data;

generating a gain-induced level correction factor for each detector channel based upon the gain correction factor; and

- 5 updating existing values of the gain and level coefficients for each detector channel using the preliminary level correction factor, the gain-induced level correction factor, and the gain correction factor for each detector channel.

10 13. The method of claim 12, wherein the steps of generating a preliminary level correction factor for each detector channel, generating a gain correction factor for each detector channel, generating a gain-induced level correction factor for each detector channel, and updating existing values of the gain and level coefficients are repeated iteratively using successive frames of input scene data such that updated values of the gain and level coefficients converge to respective stable values.

15 14. The method of claim 12, wherein the step of updating the existing values of the gain and level coefficients comprises:

 adding the preliminary level correction factor and the gain-induced level correction factor for each channel, thereby forming a sum corresponding to each detector channel;

20 subtracting the sum from the existing value of the level coefficient for each detector channel to form an updated value of said level coefficient; and

 multiplying the existing value of the gain coefficient for each channel by the gain correction factor corresponding to that channel to form an updated value of the gain coefficient for each detector channel.

25 15. The method of claim 12, wherein the step of generating a preliminary level correction factor for each channel comprises:

applying a first vertical high pass filter to the frame of input scene data to generate a frame of first high-passed data;

applying a horizontal infinite impulse response filter to the frame of first high-passed data to generate a frame of second high-passed data;

- 5 applying thresholding based upon the frame of first high-passed data and the frame of second high-passed data to generate a frame of thresholded data; and averaging the values of pixels in each row of a frame of data generated from the previous step to generate row averages to provide preliminary level correction factors.

- 10 16. The method of claim 15, further comprising the step of:
 applying a second vertical high pass filter to the row averages to generate high-passed row averages, the high-passed row averages being used as the preliminary level correction factors.

- 15 17. The method of claim 15, further comprising the step of:
 applying a vertical null-pixel filter to the frame of thresholded data prior to said averaging step to generate a frame of null-pixel-filtered data, wherein the vertical null-pixel filter identifies null pixels of the frame of thresholded data having values of zero and assigns vertically adjacent pixels within a predetermined number of pixels of the null pixels to have values of zero.

- 20 18. The method of claim 17, wherein the predetermined number of pixels is one.

19. The method of claim 15, wherein the first vertical high pass filter has a kernel of $d1 \times (-1/3, 2/3, -1/3)$ and wherein the second high pass filter has a kernel of $d2 \times (-1/3, 2/3, -1/3)$, where $d1$ and $d2$ are damping factors.

20. The method of claim 19, wherein d1 is in the range of approximately 0.5-0.95 and wherein d2 is approximately 1.0.

21. The method of claim 15, wherein the averaging is conditional averaging such that a row average is calculated if a number of non-zero pixels in
5 that row is greater than a predetermined minimum number, the row average being calculated based upon the number of non-zero pixels, and wherein the row average is given an assigned value otherwise.

22. The method of claim 21, wherein the predetermined minimum
10 number is in the range of approximately 0.25-0.8 times a number of pixels in each row.

23. The method of claim 21, wherein the assigned value is zero.

24. The method of claim 15, wherein said thresholding comprises the steps of:
for each pixel of the frame of first high-passed data, making a first
15 determination of whether an absolute value of said pixel value of the frame of first high-passed data is greater than zero and less than a first threshold value, and making a second determination of whether an absolute value of a difference between said pixel value of the frame of first high-passed data and a pixel value of a corresponding pixel of the frame of second high-passed data is less than a second
20 threshold value;

assigning a corresponding pixel value of the frame of thresholded data to have said pixel value of the frame of first high-passed data if both the first and second determinations are true; and

giving the corresponding pixel value an assigned value otherwise.

25. The method of claim 24, wherein assigned value is zero.

26. The method of claim 24, wherein the first threshold value is in the range of approximately 1-1.5 times a temporal noise value.

27. The method of claim 26, wherein the second threshold value is in
5 the range of approximately 3-4 times the temporal noise value.

28. The method of claim 12, wherein the step of generating a gain
correction factor for each detector channel comprises the steps of:
applying high-pass filtering and thresholding to the frame of input scene
data;

10 for each row of a frame of data generated from the previous step,
identifying positive pixel values and negative pixel values;
for each row of the frame of input scene data, calculating a row average
of the pixel values of the frame of input scene data corresponding to the positive
pixel values (AVG POS), and calculating a row average of the pixel values of the
15 frame of input scene data corresponding to the negative pixel values (AVG NEG);
for each row of the frame of input scene data, comparing AVG POS to
AVG NEG; and

determining a gain correction factor for each detector channel
corresponding to each row of the frame of input scene data based upon said
20 comparing AVG POS to AVG NEG.

29. The method of claim 28, further comprising the step of:
applying a vertical null-pixel filter prior to said step of identifying
positive pixel values and negative pixel values, wherein the vertical null-pixel filter
identifies null pixels of the frame of thresholded data having values of zero and

assigns vertically adjacent pixels within a predetermined number of pixels of the null pixels to have values of zero.

30. The method of claim 29, wherein the predetermined number of pixels is one.

5 31. The method of claim 26, wherein calculating a row average is conditional such that the row average is calculated if a number of non-zero pixels in that row is greater than a predetermined minimum number, the row average being calculated based upon the number of non-zero pixels, and wherein the row average is given an assigned value otherwise.

10 32. The method of claim 31, wherein the predetermined minimum number is in the range of approximately 0.25-0.8 times a number of pixels in each row.

33. The method of claim 31, wherein the assigned value is zero.

15 34. The method of claim 28, wherein said gain correction factors are preliminary gain correction factors and wherein the method further comprises the step of:

applying a high-pass filter to the array of preliminary gain correction factors.

20 35. The method of claim 34, wherein the high pass filter has a kernel of $d \times (-1/3, 2/3, -1/3)$, wherein d is a damping factor.

36. The method of claim 28, wherein said step of comparing and said step of determining together comprise the steps of:

calculating a difference between AVG POS and AVG NEG for each row
(i) of the frame of input scene data; and

assigning a value to each gain correction factor, $G(i)$, based upon the
following conditions:

- 5 if $n2 > (AVG POS) - (AVG NEG) > n1$, then $G(i) = 1 - Ginc/D$;
 if $n2 > (AVG NEG) - (AVG POS) > n1$, then $G(i) = 1 + Ginc/D$;
 if $(AVG POS) - (AVG NEG) > n2$, then $G(i) = 1 - Ginc$;
 if $(AVG NEG) - (AVG POS) > n2$, then $G(i) = 1 + Ginc$;
 if $(AVG NEG) = 0$ or if $(AVG POS) = 0$, then $G(i) = 1$; and
10 $G(i) = 1$ otherwise,
 wherein $n2 > n1$, $Ginc$ is a predetermined gain-correction step size, and
 D is a divisor factor greater than 1.

37. The method of claim 36, wherein $n2$ is approximately 4-8 times
greater than $n1$.

- 15 38. The method of claim 36, wherein $Ginc$ is in the range of
approximately 0.01-0.001 and wherein D is in the range of approximately 2-16.

39. The method of claim 36, wherein said gain correction factors,
 $G(i)$, are preliminary gain correction factors and wherein the method further
comprises the step of:

- 20 applying a high pass filter to the array of preliminary gain correction
factors, $G(i)$, to generate the gain correction factors, $G'(i)$, for the detector
channels of the scanning detector array.

40. The method of claim 12, wherein said step of generating a gain-
induced level correction factor for each detector channel comprises the steps of:

applying high-pass filtering and thresholding to the frame of input scene data to provide a frame of thresholded data;

for a frame of data generated from the previous step, identifying positive pixel values and negative pixel values;

5 calculating a total average pixel value (TOT AVG) of pixels of the frame of input scene data corresponding to said positive pixel values and said negative pixel values; and

 calculating the gain-induced level correction factor for each detector channel based upon TOT AVG and the gain correction factor for each detector
10 channel.

41. The method of claim 40, wherein the gain-induced level correction factor for each detector channel is equal to the product (TOT AVG) x (1 - gain correction factor for each detector channel).

42. The method of claim 40, further comprising the step of:
15 applying a vertical null-pixel filter to the frame of thresholded data prior to said step of identifying positive pixel values and negative pixel values, to generate a frame of null-pixel-filtered data, wherein the vertical null-pixel filter identifies null pixels of the frame of thresholded data having values of zero and assigns vertically adjacent pixels within a predetermined number of pixels of the
20 null pixels to have values of zero.

43. The method of claim 42, wherein the predetermined number of pixels is one.

44. An apparatus for providing corrected values of gain and level coefficients of a set of correction coefficients for a scanning detector array,
25 comprising:

a processor unit coupled to a scanning detector array, the processor unit being configured to:

modify first values of the gain and level coefficients using at least one frame of image data collected from out-of-focus multiple-temperature imagery by the scanning detector array; and

determine updated values of the gain and level coefficients using a scene-based non-uniformity correction (SBNUC) routine applied to scene data corresponding to focused scene imagery.

45. An apparatus for providing corrected values of gain and level coefficients of a set of correction coefficients for a scanning detector array, comprising:

a processor unit coupled to a scanning detector array, the processor unit being configured to:

generate a preliminary level correction factor for each detector channel using a frame of input scene data;

generate a gain correction factor for each detector channel using the frame of input scene data;

generate a gain-induced level correction factor for each detector channel based upon the gain correction factor; and

update existing values of the gain and level coefficients for each detector channel using the preliminary level correction factor, the gain-induced level correction factor, and the gain correction factor for each channel.